

Setup Certags - ComplyPro Label Printer without using ComplyPro Label Designer

Step 1:

Please install driver from the following source:

Global / USA	https://www.certags.com/download-links
UK / Europe	https://certags.co.uk/label-printers/complypro-down- loads/
Australia / NZ	https://certags.com.au/label-printers/complypro-down- loads/
Germany	https://certags.de/downloads/

Step 2:

Windows 7	Left click the Windows symbol on the bottom left corner, select "Devices and Printers".
Windows 10	Right click on the Windows symbol on the bottom left corner, click on Settings -> Devices -> Printers & Scanners. Here you can see the printer "BP530".

Step 3:

Click on BP530 and click "Manage" then click "Printer properties".

Select the Tab "Tools" and click on "Driver Options".

Select the tab "Regional Options" and select "Millimeter" on the bottom drop down menu.

Confirm both windows with OK.

Step 4:

Next click on "Printing preferences".

Step 5:

Select the tab "Page Setup" and click "Edit" on top.

Step 6:

Put in your label size and click OK.

Important: For Heavy Duty Clear Wrap and Economy Clear Wraps please enter width 40 mm and height 50 mm.

Step 7:

Please click on tab "Stock".

Uncheck both check marks and set the settings as follows:

BP530 Printing Preferences

Heavy Duty Clear Wrap / Economy Clear Wrap

Gap length: Total length minus 50 mm. (e.g. for 200 mm HDCW type in 150 mm)

age Setup Graphic	> Stock Opti					
Media Settings						
Use Current P	rinter Settings					
Print Method:	Thermal Trans	fer	\sim			
Media Type:	Labels With G	aps	\sim			
Label Gap:	??? mm	Black M	ark Width:	3,0 mm		
Extra Feed:	0,0 mm	Black M	ark Offset:	0,0 mm		
Media Handling						
Post-Print Action:	Cut ~					
Occurrence:	After Every La	ibel	\sim			
Interval:	1					
Position Adjustme	nts					
Use Current P	rinter Settings					
Start Position:	0,0 mm	Stop Po	sition:	23,0 mm		
BP530 Printing F	Ca Preferences	ancel	Apply	Help		
OF BP530 Printing F age Setup Graphic Media Settings Use Current Pr	Ca Preferences Stock Option	ancel	Apply	Help		
OF BP530 Printing F age Setup Graphic Media Settings Use Current Pr Print Method:	Ca Preferences s Stock Option rinter Settings Thermal Trans	ancel ancel fer	Apply	Help ×		
Of BP530 Printing F age Setup Graphic Media Settings Use Current Pr Print Method: Media Type:	Circferences Stock Option Content Settings Thermal Trans Labels With G	ancel aps	Apply	Help		
OF BP530 Printing F age Setup Graphic Media Settings Use Current Pr Print Method: Media Type: Label Gap:	Careferences s Stock Optiminater Settings Thermal Trans Labels With G 6,0 mm	ancel for About Black Mi	Apply	Help ×		
Of BP530 Printing F age Setup Graphic Media Settings Use Current Pr Print Method: Media Type: Label Gap: Extra Feed	Car Preferences S Stock Option Inter Settings Thermal Trans Labels With G 6,0 mm 0,0 mm	fer Black Mi Black Mi	Apply	Help ×		
OF BP530 Printing F age Setup Graphic Media Settings Use Current Pr Print Method: Media Type: Label Gap: Extra Feed: Media Handling	Ca Preferences IS Stock Option Inter Settings Thermal Trans Labels With G 6,0 mm 0,0 mm	nncel fer fer Black Mi Black Mi	Apply	Heip ×		
OF BP530 Printing F age Setup Graphic Outse Current Pr Print Method: Media Type: Label Gap: Extra Feed Media Handling Post-Print Action:	Cut	nncel fer Black Mi Black Mi	Apply	Help ×		
OF BP530 Printing F age Setup Graphic Media Settings Use Current Pr Print Method: Media Type: Label Gap: Extra Feed Media Handling Post-Print Action: Occurrence:	Ca Preferences S Stock Option inter Settings Thermal Trans Labels With G 6,0 mm 0,0 mm Cut After Every La	ancel fer aps Black Mi Black Mi Black Mi	Apply	3,0 mm		
OF BP530 Printing F age Setup Graphic Media Settings Use Current Pr Print Method: Media Type: Label Gap: Extra Feed. Media Handling Post-Print Action: Occurrence: Interval:	Cut Cut Cut Cut Cut Cut Cut Cut	ancel [] fer aps Black Mi Black Mi bel	Apply	Help ×		
OP OP	Cut Cut Cut Cut Cut Cut Cut Cut Cut Cut	ancel fer aps Black Mi Black Mi Black Mi	Apply	3,0 mm 0,0 mm		
OP OP	Cut Cut Cut Cut Cut Cut Cut Cut Cut Cut	ancel fer aps Black Mi Black Mi bel	Apply	3,0 mm 0,0 mm		
Official and a settings Occurrence: Interval: Orsition Adjustment Orsition and a settings	Cut Cut Cut Cut Cut Cut Cut Cut Cut Cut	ancel [pns About fer aps Black Mi Black Mi bel Stop Por	Apply	Help X 3,0 mm 0,0 mm 26,0 mm		
OP OP	Cut After Every La 1 0,0 mm	ancel	Apply	Help X 3,0 mm 0,0 mm 26,0 mm		



Step 8:

 \times

Select tab "Options" and uncheck both check marks.

Please select speed 50.80 mm/s on top and below you slide the slider to 16.

Step 9:

Click on Apply and then OK.

Vinyl Tape

Die Cut PVC Labels